



ILLUMINATING ENGINEERING SOCIETY OF NORTH AMERICA
ANNUAL AVIATION LIGHTING CONFERENCE
October 16, 2012
St. Pete Beach, Florida

Optimized LED Architecture based on a Parallel Circuit


Airfield. Our Field.

Bruno Urbaing Product Manager

Overview


- Technical information
 - The usual 6.6A architecture
 - The Parallel LED circuit
 - Components of the system
- Installation at PARIS CDG
 - General presentation of Paris CDG
 - AGL functions covered quantities
- Analysis

New AGL circuit concept



- 6.6A series architecture designed for incandescent lamps
- First LED applications: had to be compatible with existing infrastructure as part of the safety case
- But this situation is far from optimal


New AGL circuit concept



The time is right to look further: a new approach for the complete AGL concept. From the lights, up to the power supply.

- Less is more, and better!
 - Less components
 - Reduction in power consumption
 - More functionalities
 - Better distributed intelligence
- Potential possibilities:
 - PWM series circuit?
 - Parallel supply?
 - ... ?

New AGL circuit concept




Many criteria, with a different weight for each airport:


- Initial cost
- Maintenance costs
- Energy consumption
- Individual communication
- Length of circuits, type and number of fixtures

Question is complex, and cannot be solved by purely theoretical theories.

- CCR provides stabilized current (2.8 6.6A)
- In the light:
 - Over voltage protection
 - Energy storage
 - Current measurement




Electrical design - dimming



- CCR provides stabilized current (2.8 6.6A)
- In the light:
 - Over voltage protection
 - Energy storage
 - Current measurement
 - Stabilized DC voltage and current generation

 PWM to obtain the right brightness step



Advantages


- Can be retrofit into existing circuits
- Maintenance familiarity with series circuits
- Proven to be adaptable for all operational requirements heaters, individual control, failed fixture monitoring

Disadvantages

Circuit complexity (& fixture cost)

 Accurate current control in the CCR, with a second current control
 in the light


Cost



- Disadvantages (continued)
 - Overall system efficiency not optimal due to circuit complexity (losses in CCR, transfo & fixture)
 - Safety- Still a HV circuit
 - Individual control is far from optimal:

Communication on the series loop

Need for a Remote unit at each light



Possible options

Two routes are possible:



Simple:

Series circuit, with PWM current directly useable by the lights No communication

Applications:

Short circuits
Re-use of existing cables
No individual communication

Functional:

Parallel circuit, with fixed voltage Communication to the lights, for on/off, brightness and feedback


Applications:

Long circuits, mix of various types of lights
Selective switching, monitoring


Parallel LED Circuit


Parallel LED Circuit

A Sinewave Voltage adapter (the PPC) outputs a low voltage sinusoidal waveform onto which a control signal is added for on/off and brightness control to all lights




Architecture











The PPC

Parallel
Power and
Communication Unit



The PPC

- Input voltage: 230 or 400V, 50 or 60Hz
- Output Voltage: 450VAC, floating toward ground
- Nominal Power: 3kVA
- Automatic megging capability (EFD), failed fixture monitoring (LFD)
- Over current protection (input and output)
- Remote control by multiwire or J-Bus (single or redundant)
- HMI




The PPC

- Includes master card for individual communication to the lights
- Up to 123 lights per circuit
- Up to 15 independently controlled groups of lights
 - On/off
 - Brightness level
- Individual monitoring of the status of the light
- Dimensions 400 x 600 x 1085 mm
- Weight 83 kg

LPS/LPC

Led
Parallel
Straight (or Curved) Light



The LPS/LPC light

- Derived from the LTS/LTC taxiway centerline and stop bar light
- 8", installed on shallow base
- Uni- or bidirectional; green, yellow, red
- Full compliance to ICAO Annex 14
- Input voltage 360-450VAC (Wide range insures proper operation even with voltage reduction along the length of the circuit)
- Max. power consumption lower than 20W (bidirectional fixture)

The LPS/LPC light

 Includes communication module. On/Off and brightness determined by PPC command In Paris:

```
Step 1: 0.09%
Step 2: 0.85%
Step 3: 5.83%
Step 4: 26.66%
Step 5: 94.53%
(easily modifiable by software)
```

- No influence from the input voltage
- Continuous monitoring of the status of the light (LEDs + electronics) and feedback to the PPC

CB

Connection Box



The Connection Box

- Watertight device (IP67) to connect one or two LPS/LPC light units to the main trunk
- New generation 3-pole connector (based on L-823)
 - To avoid confusion in the field, this connector is specific to the parallel system
 - "Main trunk" connectors are white
- Over current protection (prevention of full circuit down due to light unit failure)

The "Main trunk" cable

- Cable is standard 3-core cable: HO7RN-F, 3G4 (approx. AWG 11)
 (same cable is used between the CB and the light)
- Thicker section may be used for long home runs, in order to reduce losses in the cable
- An algorithm allows calculating the allowable number of lights in function of the configuration (the voltage at the last light is the criterion)
- "Tree" configuration possible (e.g. apron):

Substation

installation at Paris CDG

AIRPORT TRAFFIC CONDITIONS

- ➤ Annual traffic (year 2008): ~ 500 000 ops & ~ 60 MPAX
- >Rank for ops:

n° 8 in the world, n° 1 in Europe

➤ Rank for passengers :

n° 5 in the world, n° 2 in Europe.

- ➤ Peaks in ops: Peak day: 1773 ops Peak hour: 141 ops.
- ➤ Major HUB for AIR-FRANCE/KLM.
- **➤ About 200 foreign airlines operating at CDG.**
- >Weather conditions:
 - •Low Visibility Procedures (LVP) less than 4% of time.
 - •A few snowy days.

Paris CDG




AIRPORT LAYOUT

➤ Surface area: 3200 Ha

>4 E-W parallel RWYs:

>north pair − 09R(L)/27L(R)


>south pair − 08L(R)/26R(L)



- >Taxiways: about 80 km in all.
- >2 sets of holding points:
 - >CAT 1 holding points located at 90 m from RWY centerline
 - >CAT 2/3 holding points located at 150 m from RWY centerline
- >A lot of improvements done to reinforce CAT1 holding points....


CDG GLOBAL BASIC OPERATIONS

- ➤ Arrivals on outer RWYs
- ➤ Departures on inner RWYs
- ➤ Arrival intersects take off multiple line-ups



➤ More than 250 000 arrivals per year crossing departure RWYs


CDG BASIC OPERATIONS ON THE PAIRS : West flow



AIRPORT EQUIPMENT

A-SMGCS Level 2 in service since 2003

- √4 Surface Movement Radars.
- ✓ Mode S Multi-lateration (18 antennas).
- √ Vehicle surveillance via GPS (CAPRICORN).






AIRPORT EQUIPMENT

STOP BARS

- ✓ In service only when LVP are in progress (less than 4 % of time).
- ✓Installed at CAT 3 holding points, located at 150m from RWY centerline.
- √34 controlled stop bars (a local controller has to manage 6/7 stop bars).



STOP BARS AT CDG AIRPORT



RUNWAY INCURSIONS

- Number of runway incursions
 - About 30 per year, including 3 to 5 (A+B)
 - Most of them in CAT1 (or above) conditions
 - 75 % on the two inner runways
- Preparing for traffic increase while maintaining or improving safety level
 - Potential increase in annual traffic of about 50/60%
- Need to decrease, as soon as possible, all types of runway incursions

RUNWAY INCURSIONS

 CDG Local Runway Safety Team proposed the RWSL solution, CDG Safety Review confirmed


See details on:

http://rwsl.pildo.com/

RWSL AT CDG Airport: Take-off Hold Lights (THL)



RWSL AT CDG Airport: Runway Entrance Lights (REL)




RWSL AT CDG Airport: Runway Entrance Lights (REL)



RWSL AT CDG AIRPORT ON INNER RWYs 09R/27L, 08L/26R

- ✓ **RELs** at CAT 1 holding points (e.g.: 27L). LED lights on parallel architecture
- ✓ THLs ahead of line-up taxiways used for departure.


 LED lights (red runway C/L lights 1500cd) on 6.6A series circuit



REL - Runway Entrance Lights

**** THL - Takeoff Hold Lights

- More than 2000 LPS/LPC lights installed in Paris CDG, starting April 2007:
 - on stop bars and lead-ons (65 stop bars)
 - as REL lights of the RWSL system
 - on de-icing areas
 - for taxiway applications
- About 45 PPCs
















Parallel LED Circuit - Advantages

- Overall cost reduction
 - Reduced complexity of the PPC versus CCR (no regulation)
 - No need for external communication module
 - Standard 3-core cable, not specific to AGL
- Easy installation limited costs
 - "Main trunk" takes the place of the primary loop Connection boxes take the place of the transformer
 - No need to change the infrastructure existing conduits, cans (bases) or manholes (transformer pits) can be re-used
 - In CDG, no physical separation between 6.6A primary cables (red) and parallel main trunk (black)
 - No separate communication module

Parallel LED Circuit - Advantages

Efficiency

- "Parallel" light uses less than 20W, compared to 30W for similar
 "6.6A" version
- Average current reduced (typ. 50mA per light)

Flexibility of the layout

No need for a loop - parallel supply allows "tree structure"

Improved communication

- No loop (= antenna) means less cross-talk
- Communication does not have to pass through an isolation transformer (no attenuation)

Safety

- Voltage limited to 450V
- Standard safety rules applicable

Parallel LED Circuit - Disadvantages

- Maintenance familiarity
- Individual control: requires communication signal to change intensity step
 - For applications requiring no individual communication, a simple system like APS is more adapted



Thank you for your attention

Bruno.urbaing@adb-air.com